



Advance Information

*MPC755BTPNS/D
Rev. 0, 4/2002*

*MPC755 Part Number
Specification for the
XPC755BxxxxTx Series*

*Motorola Part
Numbers Affected:*

*XPC755BRX350TD
XPC755BRX400TD
XPC755BRX350TE
XPC755BRX400TE*

This document describes part-number-specific changes to recommended operating conditions and revised electrical specifications, as applicable, from those described in the general *MPC755 RISC Microprocessor Hardware Specifications* (Order No. MPC755EC/D).

Specifications provided in this document supersede those in the *MPC755 RISC Microprocessor Hardware Specifications*, Rev. 4 or later, for the part numbers listed in Table A only. Specifications not addressed herein are unchanged. Because this document is frequently updated, refer to <http://www.motorola.com/semiconductors> or to your Motorola sales office for the latest version.

Note that headings and table numbers in this document are not consecutively numbered. They are intended to correspond to the heading or table affected in the general hardware specification.

Part numbers addressed in this document are listed in Table A. For more detailed ordering information see Section 1.10, "Ordering Information." Note that significant differences exist between Rev. 2.7 (Rev. D) and Rev. 2.8 (Rev. E) devices. All such differences are detailed in this specification.



Table A. Significant Differences from Hardware Specification by Part Number

Motorola Part Number ¹	Operating Conditions			Significant Differences from Hardware Specification
	CPU Frequency	V _{DD} ²	T _J (°C)	
XPC755BRX350TD	350 MHz	2.0 V ±100 mV	-40 to 105	Extended operating temperature; 2.0 V/1.8 V I/O voltage supported, 2.5 V I/O not supported; all nominal core voltages are 2.0 V ±100 mV; AC timing different for processor bus and L2 bus interfaces; L2 bus interface AC timing not guaranteed in 1.8 V/2.0 V mode.
XPC755BRX400TD	400 MHz			
XPC755BRX350TE	350 MHz			Extended operating temperature
XPC755BRX400TE	400 MHz			

Notes:

1. The X prefix in a Motorola PowerPC part number designates a "Pilot Production Prototype" as defined by Motorola SOP 3-13. These are from a limited production volume of prototypes manufactured, tested, and Q.A. inspected on a qualified technology to simulate normal production. These parts have only preliminary reliability and characterization data. Before pilot production prototypes may be shipped, written authorization from the customer must be on file in the applicable sales office acknowledging the qualification status and the fact that product changes may still occur while shipping pilot production prototypes.
2. Nominal. See Table 3 for recommended operating conditions

There are currently no known errata for the part numbers addressed by this document.

1.3 General Parameters

The general parameters that follow apply to the part numbers described herein:

- Core power supply 2.0 V ±100 mV DC (nominal; see Table 3 for recommended operating conditions)
- I/O power supply 1.8 V ±100 mV DC (processor bus interface only; not supported on L2 interface; **XPC755BRX350TD** and **XPC755BRX400TD** only), or 2.0 V ±100 mV DC (processor bus interface only; not supported on L2 interface; **XPC755BRX350TD** and **XPC755BRX400TD** only), or 2.5 V ±125 mV DC (**XPC755BRX350TE** and **XPC755BRX400TE** only), or 3.3 V ±165 mV DC

1.4.1 DC Electrical Characteristics

The Rev. D devices support 3.3 V and 1.8 V/2.0 V I/O voltages, but do not support the 2.5 V I/O voltages supported by Rev. E devices. Note that Rev. E devices do not support 1.8 V/2.0 V I/O. Table 2 describes the input threshold voltage settings. Though unchanged from the *MPC755 RISC Microprocessor Hardware Specifications*, input threshold voltage settings for Rev. E devices are also included for clarity.

Table 2. Input Threshold Voltage Setting

BVSEL Signal	Processor Bus Interface Voltage		L2VSEL Signal	L2 Bus Interface Voltage	
	XPC755RX350TD XPC755RX400TD	XPC755RX350TE XPC755RX400TE		XPC755RX350TD XPC755RX400TD	XPC755RX350TE XPC755RX400TE
0	1.8 V or 2.0 V	N/A	0	1.8 V or 2.0 V	N/A
1	3.3 V	2.5 V or 3.3 V	1	3.3 V	2.5 V or 3.3 V

Caution: The input threshold selection must agree with the $OV_{DD}/L2OV_{DD}$ voltages supplied.

Table 3 provides the recommended operating conditions for Rev. D devices. Though unchanged from the *MPC755 RISC Microprocessor Hardware Specifications*, recommended operating conditions for Rev. E devices are also included for clarity.

Table 3. Recommended Operating Conditions¹

Characteristic	Symbol	Recommended Value			Unit	Notes
		XPC755RX350TD XPC755RX400TD	XPC755RX350TE	XPC755RX400TE		
Core supply voltage	V_{DD}	2.0 ±100 mV	1.9-2.0 ±100 mV	2.0 ±100 mV	V	2
PLL supply voltage	AV_{DD}	2.0 ±100 mV	1.9-2.0 ±100 mV	2.0 ±100 mV	V	2
L2 DLL supply voltage	$L2AV_{DD}$	2.0 ±100 mV	1.9-2.0 ±100 mV	2.0 ±100 mV	V	2
Processor bus supply voltage	BVSEL = 0	OV_{DD}	1.8 ±100 mV or 2.0 ±100 mV	N/A	V	
	BVSEL = 1	OV_{DD}	3.3 ±165 mV	3.3 ±165 mV or 2.5V ±125 mV	V	
L2 bus supply voltage	L2VSEL = 0	$L2OV_{DD}$	1.8 ±100 mV or 2.0 ±100 mV	N/A	V	
	L2VSEL = 1	$L2OV_{DD}$	3.3 ±165 mV	3.3 ±165 mV or 2.5V ±125 mV	V	
Die junction temperature	T_j	-40 to 105			°C	

Notes:

1. These are the recommended and tested operating conditions. Proper device operation outside of these conditions is not guaranteed.
2. 2.0 V nominal.

Table 6 provides the DC electrical specifications for Rev. D devices. Though unchanged from the *MPC755 RISC Microprocessor Hardware Specifications*, the DC electrical specifications for Rev. E devices are also included for clarity. Also note that the AC timing specifications given for Rev. E devices are guaranteed for both 2.5 V and 3.3 V operation.

Table 6. DC Electrical Specifications

At recommended operating conditions (see Table 3)

Characteristic	Nominal Bus Voltage ¹	Symbol	Min	Max	Unit	Notes
Input high voltage (all inputs except SYSCLK)	1.8/2.0	V _{IH}	$0.65 \times (L2)OV_{DD}$	$(L2)OV_{DD} + 0.3$	V	2,3,4
	2.5		1.6	$(L2)OV_{DD} + 0.3$		5
	3.3		2.0	$(L2)OV_{DD} + 0.3$		2,3
Input low voltage (all inputs except SYSCLK)	1.8/2.0	V _{IL}	-0.3	$0.35 \times (L2)OV_{DD}$	V	2,4
	2.5		-0.3	0.6		5
	3.3		-0.3	0.8		
SYSCLK input high voltage	1.8/2.0	KV _{IH}	1.5	$OV_{DD} + 0.3$	V	4
	2.5		1.8	$OV_{DD} + 0.3$		5
	3.3		2.4	$OV_{DD} + 0.3$		
SYSCLK input low voltage	1.8/2.0	KV _{IL}	-0.3	0.2	V	4
	2.5		-0.3	0.4		5
	3.3		-0.3	0.4		
Output high voltage, I _{OH} = -6 mA	1.8/2.0	V _{OH}	$(L2)OV_{DD} - 0.45$	—	V	4
	2.5		1.7	—		5
	3.3		2.4	—		
Output low voltage, I _{OL} = 6 mA	1.8/2.0	V _{OL}	—	0.45	V	4
	2.5		—	0.45		5
	3.3		—	0.4		

Notes:

1. Nominal voltages; see Table 3 for recommended operating conditions.
2. For processor bus signals, the reference is OV_{DD} . $L2OV_{DD}$ is the reference for the L2 bus signals.
3. Excludes test signals (LSSD_MODE, L1_TSTCLK, L2_TSTCLK) and IEEE 1149.1 boundary scan (JTAG) signals.
4. XPC755BRX350TD and XPC755BRX400TD only.
5. XPC755BRX350TE and XPC755BRX400TE only.

1.4.2.2 Processor Bus AC Specifications

All Rev. D part numbers have slower AC timing characteristics than later revisions of the part. The affected processor bus AC timing specifications are given in Table 10. Though unchanged from the *MPC755 RISC Microprocessor Hardware Specifications*, the AC timing characteristics for Rev. E devices are also included for clarity.

Table 10. Processor Bus AC Timing Specifications

At recommended operating conditions (see Table 3)

Parameter	Symbol	XPC755BRX350TD XPC755BRX400TD		XPC755BRX350TE XPC755BRX400TE		Unit
		Min	Max	Min	Max	
Input Hold Times: $\overline{\text{TLBISYNC}}$, $\overline{\text{MCP}}$, $\overline{\text{SMI}}$	t_{XKH}	0.6	—	0.6	—	ns
Input Hold Times: All Inputs except $\overline{\text{TLBISYNC}}$, $\overline{\text{MCP}}$, $\overline{\text{SMI}}$		0.6	—	0.2	—	
Valid Times: All Outputs	t_{KHOV}	—	4.5	—	4.1	ns

1.4.2.4 L2 Bus AC Specifications

The AC timing characteristics of the L2 bus interface in 3.3 V mode are slower for Rev. D than for Rev. E devices. Additionally, the AC timing of the L2 interface is not guaranteed or tested in 1.8 V/2.0 V mode for Rev. D devices and does not meet these specifications. The L2 interface output drivers may display a non-linear, stepped behavior when switching that prolongs the rise and fall times in this mode. This behavior is dependent on $L2OV_{\text{DD}}$, the impedance of the circuit board, and operating conditions of the processor. In a worst-case device, at $L2OV_{\text{DD}} = 1.8 \text{ V}$ and $T_j = 105^\circ\text{C}$, the driver output impedance is 55Ω ; at $L2OV_{\text{DD}} = 2.0 \text{ V}$ and $T_j = 105^\circ\text{C}$, the driver output impedance is 47Ω . The non-linear behavior results when the driver output impedance is greater than the board impedance and can cause reflected wave switching instead of incident wave switching. The voltage level at which the step will occur is $V_{\text{step}} = L2OV_{\text{DD}} \times [Z_{\text{board}} / (Z_{\text{out}} + Z_{\text{board}})]$. If V_{step} is less than the input high threshold voltage of the SRAM, the SRAM will not recognize a logical high on a given signal until the reflected wave arrives. The time delay between the arrival of the incident wave and the reflected wave is determined solely by the propagation delay of the signal. Because of these issues, Motorola does not recommend or support the use of the L2 bus interface of Rev. D devices in 1.8 V/2.0 V mode. Table 12 provides the L2 bus interface AC timing specifications for the Rev. D devices described in this document when the L2 bus interface is in 3.3 V mode only; note Rev. D devices do not support 2.5 V I/O. Though unchanged from the *MPC755 RISC Microprocessor Hardware Specifications*, the L2 Bus AC timing characteristics for Rev. E devices are also included for clarity. Also note that the L2 Bus AC timing specifications given for Rev. E devices are guaranteed for both 2.5 V and 3.3 V operation and that Rev. E devices do not support 1.8 V/2.0 V mode.

Table 12. L2 Bus Interface AC Timing Specifications

At recommended operating conditions (see Table 3)

Parameter	Symbol	XPC755BRX350TD XPC755BRX400TD		XPC755BRX350TE XPC755BRX400TE		Unit	Notes
		Min	Max	Min	Max		
Setup Times: Data and parity	t_{DVL2CH}	1.5	—	1.2	—	ns	2
Input Hold Times: Data and parity	t_{DXL2CH}	0.5	—	0	—	ns	2
Valid Times: All outputs when L2CR[14–15] = 00 All outputs when L2CR[14–15] = 01 All outputs when L2CR[14–15] = 10 All outputs when L2CR[14–15] = 11	t_{L2CHOV}	—	3.6	—	3.1	ns	3, 4
		—	3.8	—	3.2		
		—	4.0	—	3.3		
		—	4.2	—	3.7		
L2SYNC_IN to high impedance: All outputs when L2CR[14–15] = 00 All outputs when L2CR[14–15] = 01 All outputs when L2CR[14–15] = 10 All outputs when L2CR[14–15] = 11	t_{L2CHOZ}	—	3.5	—	2.4	ns	3, 5
		—	4.0	—	2.6		
		—	4.2	—	2.8		
		—	4.5	—	3.0		

Notes:

- All input specifications are measured from the midpoint of the signal in question to the midpoint voltage of the rising edge of the input L2SYNC_IN. Input timings are measured at the pins.
- All output specifications are measured from the midpoint voltage of the rising edge of L2SYNC_IN to the midpoint of the signal in question. The output timings are measured at the pins. All output timings assume a purely resistive 50-Ω load.
- The outputs are valid for both single-ended and differential L2CLK modes. For pipelined registered synchronous BurstRAMs, L2CR[14–15] = 01 or 10 is recommended. For pipelined late write synchronous BurstRAMs, L2CR[14–15] = 11 is recommended.
- Guaranteed by design and characterization.

1.10 Ordering Information

1.10.1 Part Numbers Addressed by This Specification

Table 20 provides the ordering information for the MPC755 parts described in this specification.

Table 20. Part Numbering Nomenclature


XPC	755	B	xx	nnn	x	x
Product Code	Part Identifier	Process Descriptor	Package	Processor Frequency¹	Application Modifier	Revision Level
XPC ²	755	B = HiP4DP	RX = CBGA	350 400	T: 2.0 V ±100 mV -40° to 105°C	D: 2.7; PVR = 0008 3203 E: 2.8; PVR = 0008 3203

Notes:

1. Processor core frequencies supported by parts addressed by this specification only. Parts addressed by other specifications may support other maximum core frequencies.
2. The X prefix in a Motorola part number designates a "Pilot Production Prototype" as defined by Motorola SOP 3-13. These are from a limited production volume of prototypes manufactured, tested, and Q.A. inspected on a qualified technology to simulate normal production. These parts have only preliminary reliability and characterization data. Before pilot production prototypes may be shipped, written authorization from the customer must be on file in the applicable sales office acknowledging the qualification status and the fact that product changes may still occur while shipping pilot production prototypes.

1.10.3 Part Marking

Parts are marked as the example shown in Figure 29.



BGA

Notes:

- MMMMMM is the 6-digit mask number.
- ATWLYYWWA is the traceability code.
- CCCCC is the country of assembly. This space is left blank if parts are assembled in the United States.

Figure 29. Part Marking for BGA Device

Document Revision History

Table B provides a revision history for this hardware specification.

Table B. Document Revision History

Revision No.	Substantive Change(s)
0	Initial release.

How to Reach Us:

Home Page:

www.freescale.com

E-mail:

support@freescale.com

USA/Europe or Locations Not Listed:

Freescale Semiconductor
 Technical Information Center, CH370
 1300 N. Alma School Road
 Chandler, Arizona 85224
 +1-800-521-6274 or +1-480-768-2130
support@freescale.com

Europe, Middle East, and Africa:

Freescale Halbleiter Deutschland GmbH
 Technical Information Center
 Schatzbogen 7
 81829 Muenchen, Germany
 +44 1296 380 456 (English)
 +46 8 52200080 (English)
 +49 89 92103 559 (German)
 +33 1 69 35 48 48 (French)
support@freescale.com

Japan:

Freescale Semiconductor Japan Ltd.
 Headquarters
 ARCO Tower 15F
 1-8-1, Shimo-Meguro, Meguro-ku,
 Tokyo 153-0064
 Japan
 0120 191014 or +81 3 5437 9125
support.japan@freescale.com

Asia/Pacific:

Freescale Semiconductor Hong Kong Ltd.
 Technical Information Center
 2 Dai King Street
 Tai Po Industrial Estate
 Tai Po, N.T., Hong Kong
 +800 2666 8080
support.asia@freescale.com

For Literature Requests Only:

Freescale Semiconductor Literature Distribution Center
 P.O. Box 5405
 Denver, Colorado 80217
 1-800-441-2447 or 303-675-2140
 Fax: 303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

RoHS-compliant and/or Pb- free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb- free counterparts. For further information, see <http://www.freescale.com> or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to <http://www.freescale.com/epp>.

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document. Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.



MPC755BTPNS/D

**For More Information On This Product,
 Go to: www.freescale.com**